



lux

Yet another bright idea!



PREMIUM RADIO PIR FOR EFFECTIVE SECURITY + BRIGHT NIGHT-LIGHT FOR SAFETY

Ness LUX

Premium Radio PIR with Night-Light

Ness LUX Radio PIR – a unique wireless motion detector with a white LED night-light.

With all the features and benefits of Ness premium radio detectors, LUX features 15m x 15m detection coverage, look-down creep zone, high RF immunity, white light immunity, adjustable range, adjustable pulse count and extremely long battery life.

For safety and convenience, LUX's night-light function provides a motion-activated cone of light to help you find your way at night, while the built-in ambient light sensor helps save power by enabling the night-light only in the dark.

Ness LUX's "capsule" design protects sensitive electronic components and provides easy access to the dipswitches and batteries.

Ness LUX is supplied with long-life lithium batteries with an expected service life of up to 10 years service under normal conditions.

LUX PET AWARE model with unique Opposing Fields lens technology has a superior ability to discriminate between household pets and unwanted human intruders allowing you to secure your home with your pets indoors.

- 15m x 15m wide angle coverage
- Look down 'Creep Zone' (106-168)
- White LED motion activated night-light
- Adjustable Pulse Count
- Adjustable Range
- High R.F. and E.S.D. immunity
- High white light immunity
- SAWR stabilised radio transmitter
- Capsule design with sealed electronics
- Front cover tamper protection
- Long life Lithium batteries supplied
- Low battery warning signal
- Hourly Supervision radio signals
- Includes wall mounting bracket
- Optional ceiling bracket available
- LUX PET AWARE model allows you to secure your home with your pets indoors

lux



PREMIUM RADIO PIR FOR EFFECTIVE SECURITY + BRIGHT NIGHT-LIGHT FOR SAFETY



Fully encapsulated electronics module for safety and security

Includes convenient wall mount swivel bracket

Optional Deluxe Swivel Bracket for wall or ceiling mounting (Part No. 106-169)

LUX PET AWARE has high sensitivity to large targets and excellent rejection of pets

Specifications

Dimensions	112(h) x 72(w) x 48(d) mm
Mounting height	2.1m – 2.4m
Coverage	Up to 15m x 15m @ 90°
Detector zones	20 dual element zones
Pulse count	Selectable 1–2 or 3–4
Range	Selectable High/Low. 15m max./12m max.
Sensor	Dual element pyroelectric
Alarm indication	Blue alarm LED
Night-Light	White LED with adjustable threshold / Dark-enabled / Motion activated
Night-Light duration	PIR reset time + 10 sec / Typically on for 15–20 sec after a single trigger Remains lit during constant motion
Pet Immunity (Pet Aware model)	Single pet up to 18kg or multiple pets up to 10kg total
Alarm duration	5 seconds
Warm up duration	30 seconds
Operating voltage	3V DC
Battery	2 x CR123A Lithium
Quiescent current	< 14µA
Radio frequency	304MHz / 868MHz depending on region
Transmit power	100µW
Compatibility	All Ness radio-enabled control panels, Ness MCR receiver, Ness SCR receiver

Ordering Information

106-168 Ness LUX Radio PIR 304MHz
106-170 Ness LUX Radio PIR PET AWARE 304MHz
106-169 Ness LUX Deluxe Swivel Bracket

868MHz models available for export markets.



Innovative Electronic Solutions
www.nesscorporation.com



NSW Ph 02 8825 9222 | sales@ness.com.au | VIC Ph 03 9875 6400 | nessmelb@ness.com.au | QLD Ph 07 3399 4910 | nessbris@ness.com.au | WA Ph 08 9328 2511 | nessper@ness.com.au | SA Ph 08 8152 0000 | adelaide@ness.com.au

© 2012 Ness Corporation Pty Ltd ABN 28 069 984 372. Photos are used for illustrative purposes only. Design and specifications may vary. See the Ness Corporation web site for full warranty details.